

# RT BE42-ST



## Performance features

- + Acoustic signal operational standby ON / OFF
- + Display: Operational standby, alarm triggered and fault
- + Function: SHEV OPEN, SHEV Reset
- + Indicator diode blinks for SHEV alarm if acoustic signal is not operational

## Technical data

### RT BE42-ST

<b>Input voltage</b>	18 ... 28 V DC
<b>Loudness</b>	75 dB
<b>Temperature range</b>	-5 °C ... +40 °C
<b>W x H</b>	105 x 115 mm
<b>Weight</b>	0.09 kg
<b>Art. No.</b>	30.435.12