

# RT BE42-Z



## Performance features

- + Can be used only in conjunction with standard SHEV operation panel and UM 41 transfer module
- + For 2-wire cables
- + Function: SHEV OPEN
- + Display: Operational standby and alarm triggered
- + With indicator

## Technical data

RT BE42-Z

<b>Input voltage</b>	18 ... 28 V DC
<b>Temperature range</b>	-5 °C ... +40 °C
<b>W x H</b>	105 x 115 mm
<b>Weight</b>	0.05 kg
<b>Art. No.</b>	30.435.62