

# RT BE45-1



## Performance features

- + Can be used as main or auxiliary control panel
- + Display: Operational standby, alarm triggered and fault
- + Function: SHEV OPEN, SHEV Reset

## Technical data

RT BE45-1

<b>Input voltage</b>	18 ... 28 V DC
<b>Temperature range</b>	-5 °C ... +40 °C
<b>W x H</b>	105 x 115 mm
<b>Weight</b>	0.05 kg
<b>Art. No.</b>	66.103.04